


SEMCO® 285-B battery powered mixer

Always remember to remove battery before attempting to service the tool

Symptom	Possible cause	Recommended action
Nothing happens when power trigger is pulled	<ul style="list-style-type: none"> • Battery discharged • Battery not fully installed • Check to ensure the sealant cartridge and retainer have been installed correctly • Speed control setting is too low • Battery or tool terminals are bent or damaged 	<ul style="list-style-type: none"> • Recharge battery • Push battery on fully, until it clicks • Unscrew retainer and check cartridge installation • Adjust speed control as required • Return to <i>Semco</i> for repair
The mixer stalls during use	<ul style="list-style-type: none"> • Battery discharged • Cured material in cartridge • Material is too cold 	<ul style="list-style-type: none"> • Recharge battery • Remove cured material • Warm material to recommended mixing temperature
<p>Battery does not charge</p>  <p><i>Attempt to determine if it is the battery or the charger which is faulty by testing battery with known good charger and/or by testing charger with known good battery</i></p>	<ul style="list-style-type: none"> • Battery is either too hot or too cold • Charger is not powered • Battery not properly seated on charger • Defective battery or charger 	<ul style="list-style-type: none"> • Allow battery to return to allowable temperatures • Check power source and ensure red power light is illuminated on charger • Remove and properly reseal battery • Contact PPG <i>Semco</i> (or ASC) for repair or replacement
Mixer is not stable on the flat surface	<ul style="list-style-type: none"> • Suction cup or bumper is missing or damaged 	<ul style="list-style-type: none"> • Contact PPG <i>Semco</i> (or ASC) for replacement

SEMCO® 285-B battery powered mixer

For industrial use only. Keep away from children.

For emergency medical information call +1 (800) 228-5635.

Semco is a trademark of PRC-DeSoto International Inc., registered with the U.S. Patent Office.

All recommendations, statements, and technical data contained herein are based on tests we believe to be reliable and correct, but accuracy and completeness of said tests are not guaranteed and are not to be construed as a warranty, either expressed or implied. User shall rely on his own information and tests to determine suitability of the product for the intended use and assumes all risks and liability resulting from his use of the product. Seller's and manufacturer's sole responsibility shall be to replace that portion of the product of this manufacturer which proves to be defective. Neither seller nor manufacturer shall be liable to the buyer or any third person for any injury, loss, or damage directly or indirectly resulting from use of, or inability to use, the product. Recommendations or statements other than those contained in a written agreement signed by an officer of the manufacturer shall not be binding upon the manufacturer or seller.

Printed in the U.S.A

Bergdahl Associates, Inc.
2990 Sutro Street
Reno, NV 89512-1616

Phone: +1 775 323-7542

Issue Date: 12/19
Supersedes: New
Lit: